

S6 25-60kW and 30kW 208 Commercial Inverters Compatibility for North America

S6-GC(25-60)K-US & S6-GC30K-LV-US

**Three-Phase Commercial Inverters
25, 33, 36, 40, 50 and 60kW 480 VAC &
30kW 208/240VAC 180-1000VDC**



- Integrated module-level rapid shutdown transmitter, lockout/tagout DC switches and AC disconnect
- Wide voltage range and low startup voltage for optimum performance
- High input current supports larger modules and reduces up-front installation costs
- 3/4 MPPT design enhances design flexibility
- Separate AC wiring box for simplified operations and maintenance
- Type 4X Anti-Corrosion level enclosure
- When ordering the below, ensure the appropriate identifier is added to the SKU (e.g. -APST, -RSS, -NEPT)

Brand -SKU	Receiver Model	Number of PV Module Inputs	Rapid Shutdown	Module-Level Monitoring	Module-Level Optimization
APsmart -APST	RSD-S-PLC-A	1	✓	X	X
	RSD-D-15	2	✓	X	X
	RSD-D-20	2	✓	X	X
Tigo Energy -RSS	TS4-A-F	1	✓	X	X
	TS4-A-2F	2	✓	X	X
	TS4-A-O*	1	✓	✓	✓
NEP -NEPT	PVG-2	2	✓	✓**	X
	PVG-3	3	✓	✓**	X

*Tigo CCA must be installed externally. Tigo monitoring must be used for module-level monitoring.

**Use Fomware datalogger for module-level data monitoring with NEP

S6 30K 208
Product Page & Downloads



S6 25-60K
Product Page & Downloads



Key Notes

1. Please contact ussales@solisinverters.com for the Ordering Guide, which provides instructions on how to order the inverter with the correct internal transmitter.
- Note:** Transmitters and receivers installed must be of the same brand. Mixing components of different brands in the same system will void the inverter warranty.
2. The inverter has ports for an external switch to be connected. These ports are in series with the switch on the inverter wire box. Please see the manual for more details.
3. The RSD signal transmitter comes with the inverter. The RSD receivers are all sold separately. Please contact your local distributor for assistance with procurement.
4. Installing components not on this list will void the inverter warranty. Solis is not responsible for the quality or the warranty of the rapid shutdown components.
5. NEP standard RSD receivers are 15A (20A models are available on request).